



Powering Business Worldwide

pe.eaton.com

CH 3/4-inch main loadcenter

CH6L3125FP

UPC:782114229248

Dimensions:

- **Height:** 3.56 IN
- **Length:** 13 IN
- **Width:** 11 IN

Notes: Suitable for use as service equipment when not more than two service disconnecting means are provided or when not more than six service disconnecting means are provided and when not used as a lighting and appliance panelboard

Warranties:

- Limited lifetime

Specifications:

- **Type:** Main lug only
- **Amperage Rating:** 125A
- **Box Size:** 7
- **Bus Material:** Copper
- **Cover:** Cover not included
- **Enclosure:** NEMA 1
- **Enclosure Material:** Metallic
- **Feed Type:** Overhead or underground
- **Main Circuit Breaker:** CH
- **Main Lug Wire Size:** #14-1/0 AWG
- **Mounting:** Flush
- **Number Of Circuits:** 6
- **Number Of Wires:** Four-wire
- **Phase:** Three-phase
- **Voltage Rating:** 120/240V, 208Y/120, or 240V

Supporting documents:

- [Cutler-Hammer Type CH and BR Loadcenters - Instructions](#)
- [Eatons Volume 1-Residential and Light Commercial](#)



- [Type CH Circuit Breakers and Loadcenters](#)
- [Eaton Specification Sheet - CH6L3125FP](#)

Certifications:

- UL 50
- UL 67

Product compliance: No Data

© 2016 Eaton. All rights reserved.