

SPECIFICATION SHEET

600 & SA200 SERIES OUTDOOR PLUG-IN DIGITAL TIMER



APPLICATIONS

- Automatically turn ON/OFF outdoor lighting.
- Save energy. Don't run lights all night.
- Match dusk On with light activated timer.

FEATURES

DIGITAL TIMER:

7 day programming.
Manual Daylight Savings.
Random feature for lived in look.
Battery Back-up for power outages.

PHOTO-TIMERS:

Dusk to Dawn operation.
Set a fixed time off before Dawn.
Battery Back-up for power outages.

LIGHT ACTIVATED TIMERS:

TIMER REPEAT SCHEDULE: Daily turns on at dusk.

VARIABLE TIMING: Choose a countdown time to turn Off from 1 to 9 hours after dusk.

654A USER SELECT MODE: Start countdown at any time and repeats daily.



621D & 631D
(621D without photocell)



611D



SA204



654A

ORDERING INFO & CONTACT RATINGS

CAT. NO.	UPC CODE	RATINGS	NO. OF OUTLETS (P)	TYPE OF PLUG	DESCRIPTION	VARIABLE TIMING SEGMENTS
621D	16056	125 VAC, 15A, 1875W General Purpose	2	Grounded	Digital Outdoor Timer	7 On/Off pairs. Schedule for each day of week
611D	16018	125VAC, 15A, 1875W Resistive	1	Grounded	Digital Outdoor Photo-Timer	Photocell Turns on at Dusk and off at Dawn
631D	16027	125VAC, 1000W Tungsten 125VAC, 8A Ballast 125VAC, 1/2HP	2	Grounded	Digital Outdoor Photo-Timer	or off at a pre-set time
SA204*	16561	120VAC 8A Resistive 120VAC 600W Tungsten	2	Grounded	Light Activated Landscape Timer	Turns on at Dusk and countdown off 1 through 9 hours later
654A	16025	125VAC 15A General Purpose, 125VAC 15A Resistive, 125VAC 625W Tungsten 125VAC 1/3HP, TV-5	2	Grounded	Light Activated Outdoor Lighting Timer or User Selected Daily Repeat	Turns on at Dusk and countdown off 1 through 9 hours later. Includes user select mode.

* ETL listed for U.S. and Canada.



NOTE: "▲" = Indicates outlet location.