

## SPECIFICATION SHEET

### SA300 Series Zip-Set™ DIGITAL TIMER

#### APPLICATIONS

- Automatically turn ON/OFF outdoor lighting.
- Save energy. Turn ON adjusts to sunset daily. No need to run lights all day & night.
- Provide all-night security.

#### FEATURES

##### SCHEDULING:

Choose sunset or 7 day timer modes.

- Zip-Set™ turns lights ON at sunset & OFF at countdown or preset time.
- 7 day weekly programming. 7-5-2 settings for full week, weekdays, and weekends.
- Option to set with one of three ON/OFF programs.

##### EASY SET-UP:

Fast programming with Zip-Set™ One-Step™ set-up. Just enter your area code.

##### DAYLIGHT SAVINGS:

Manual adjustment.

##### RANDOM SETTING:

Give the 'lived in' look as times are varied each day.

##### POWER OUTAGE BACKUP:

Battery back-up for power outages. Supplied with two CR2032 batteries.

##### OVERRIDE:

Manual ON/TIMER switch.

##### COLOR:

Grey.

##### MOUNTING:

SA300 Series: Indoor surface mount.  
SA400: Indoor/outdoor surface mount.

##### WIRING:

Terminal Range #8 - #16AWG.

##### INPUT VOLTAGE:

SA300 Series: 120VAC 60 Hz.  
SS400: 120/277VAC 60 Hz.



SA400

SA300

#### ORDERING INFO

CAT. NO.	UPC CODE	INPUT SUPPLY (VAC) 60Hz	COLOR
SA300	16546	120	SPST
SA306	16549	120	DPST
SA400	16552	120/277	SPST

#### CONTACT RATINGS

TYPE	VOLTAGE (VAC)	RATING
Resistive	120*	40A
Inductive	120*	40A
Tungsten	120*	40A
Incandescent	120*	40A
Motor	120	11/2HP
SA400	120/277	-