

Project:		
Fixture Type:		
Location:		
Contact:		

HELM

Wall or ceiling mounted · Damp location listed





Description:


Helm is a uniquely styled series with design flexibility. This contemporary square fixture has an acrylic diffuser with architectural detail. Can mount to ceiling or wall. Three-light LED fixture. 3000K, 90+CRI 1,211 lumens per module.

Specifications:

- · Brushed Nickel (-09) (plated)
- · Steel construction
- · White acrylic diffuser
- 120VA replaceable LED Module (part # 93053641)
- · Dimmable to 10% brightness (See Dimming Notes)
- · Back plate covers a standard 4" hexagonal recessed outlet box
- · Mounting strap for outlet box included
- · 6" of wire supplied
- · Complies with "Americans with Disabilities Act" ADA
- · ENERGY STAR® qualified

Performance:

Number of Modules	3
Input Power	17w
Input Voltage	120 V
Input Frequency	60 Hz
Lumens/LPW	1211/71.2 (LM-79) per module
ССТ	3000 K
CRI	90
Life (hours)	60,000 (L70/TM-21)
EMI/RFI	FCC Title 47, Part 15, Class B
Min. Start Temp	-30 °C
Max. Operating Temp	30 °C
Warranty	5 year warranty
Labels	cCSAus Damp location listed
	ENERGY STAR® qualified



Images:



Dimensions:

Square: 18" Height: 3-3/4" Depth: 3-3/4" H/CTR: 9"

Glass

Width: 15-13/16" Height: 3-5/8"



HELM





P3449-0930K9

Dimming Notes:

P3449-0930K9 is designed to be compatible with many ELV/Reverse Phase controls.

The following is a partial list of known compatible dimmer controls.

Dimming Controls

Lutron Diva DVELV-300P

Lutron Nova T NTELV-300

Lutron Diva DVELV-300P

Luton Caseta

Lutron Ariadni AY-600P

Leviton Illumatech IPI06-1LZ

Lutron Lumea LG-603PG

Leviton SureSlide 6672

Leviton SureSlide 6674

Lutron Ariadni AYCL-153P

Lutron Skylark Contour CTCL-153P

Lutron Diva DVCL-153P

Pass & Seymour Harmony DCL453PTCCCV6

Lutron Toggler TGCL-153P

Lutron Maestro MACL-153M

Lutron Ariadni AYLV-600P

Lutron Maestro MA-600

Lutron NOVA T NTLV-600

lutron Maestro MAELV-600

Lutron spacer/system SPSELV-600

Lutron Renoir II AWRMG-EAW

Dimming capabilities will vary depending on the dimmer control, load, and circuit installation. Always refer to dimmer manufacturer instructions or a controls specialist for specific requirements.

Dimmer control brand names where identified above are trade names or registered trademarks of each respective company.